

## Programmable Attenuators

### HA Series

The HA series attenuators are high-resolution, extended-range, programmable attenuators ideal for testing power meters and for general test and laboratory work. The HA attenuators have a nominal resolution of 0.01 dB (0.001 dB for the HA1 series) and an extended attenuation range of 100 dB. The standard operating wavelength is 1200-1700 nm (750-1700 nm is available to use with a reduced attenuation range of 60 dB for the HA9W attenuator).

The HA1 attenuator is a single-mode, ultra-high resolution, and programmable attenuator ideal for bit error rate testing and general laboratory work.

The new JDS Uniphase HA2 Programmable Optical Attenuator provides a wavelength dependence of  $\pm 0.05$  dB and input power up to 1W (30dBm). The HA2 is suitable for a variety of applications including amplifier testing and DWDM system characterization.

HA attenuators are ideal for use in such demanding applications as multichannel AM systems and high bit-rate digital pulse code modulation (PCM) systems. Discrete internal optical reflections are minimized to better than 60 dB, and cavity effects are virtually eliminated. All HA attenuators are offered with high return loss and low spectral ripple for CATV AM systems.

The inherently linear design of these attenuators, combined with built-in calibration and offset functions, allows the user to match the display to an optical power meter over a wide power range. This feature is useful in tests requiring control of the absolute optical power source for the test device. The built-in beam blocking switch provides fast access from any attenuation setting to infinite attenuation (> 90 dB).



### → Key Features & Benefits

- 100 dB range*
- 0.01 or 0.001 dB resolution*
- 0.01 dB repeatability*
- Accuracy of  $\pm 0.1$  dB*
- Typical polarization dependent loss (PDL) of 0.03 dB*
- 1200-1700 nm or 750-1700 nm wavelength ranges*
- Built-in beam block switch*
- GPIB and RS232 remote control*
- Single-mode or multimode fiber*
- SCPI compatible command set*
- Optional couplers or switches*
- Optional universal connector adapter*
- High power input of 1000 mW*
- Wavelength dependence of less than  $\pm 0.05$  dB over 1530-1625 nm range*
- CE and cULus compliant*

### → Applications

- Precise optical power control*
- Power meter linearity calibration*
- Analog transmission tests*
- Bit error rate tests*
- Loss simulation in fiberoptic links EDFA output power characterization*



**Insist on performance. We do.**

Front panel access provides the option of increasing functionality through the addition of other devices, such as couplers or switches. The 5 V driver key on the front panel (connected to the 5 V driver on the back) acts as a toggle for an external or internal (if installed) switch.

The HA9 and HA1 attenuators can be fitted with 2/98, 10/90, 30/70, or 50/50 couplers. Optional built-in couplers or switches provide an output tap or access to two inputs or outputs. Units can be fitted with front panel or back panel mounted PC or APC universal connector adapters (UCAs). Both models have a SCPI/HP8156A compatible command set and can be controlled from the front panel keyboard or by the GPIB or RS232 interfaces.

## Technical Specifications

PARAMETER	HA1	HA9	HA9W	HA9P	HA2
Operating wavelength range	1200-1700 nm	1200-1700 nm	750-1700 nm	980-1100 nm	1280-1670 nm
Attenuation <sup>1</sup> range	100 dB	100 dB	60 dB	60 dB	50 dB
resolution	0.001 dB	0.01 dB	0.01 dB	0.01 dB	0.01 dB
repeatability <sup>2</sup>	± 0.01 dB	± 0.01 dB	± 0.01 dB	± 0.01 dB	± 0.01 dB
change rate	< 2.5 s	< 2.5 s	< 1.5 s	< 1.5 s	< 1.5 s
accuracy <sup>3</sup>	0-100 dB	0-100 dB	0-60 dB	0-60 dB	0-50 dB
	± 0.1 dB	± 0.1 dB	± 0.1 dB	± 0.1 dB	± 0.1 dB
Insertion loss <sup>4,5,6</sup> single-mode (SM)	< 1.5 dB	< 1.5 dB	< 5.0 dB	NA	< 1.0 dB <sup>8</sup>
multimode (MM), 50/125µm	NA	< 2.2 dB	< 3.2 dB	NA	NA
MM, other	NA	< 2.9 dB	< 3.9 dB	NA	NA
Flexcor 1060	NA	NA	NA	< 2.5 dB	NA
Return loss <sup>4,5</sup> SM	NA	> 45 dB	> 45 dB	NA	> 50 dB
SM, analog <sup>7</sup>	> 60 dB	> 60 dB	> 60 dB	NA	NA
MM, 50/125 µm	NA	> 35 dB	> 35 dB	NA	NA
MM, other	NA	> 30 dB	> 30 dB	NA	NA
Flexcor 1060	NA	NA	NA	> 60 dB	NA
Wavelength dependence <sup>4,9</sup> (1530-1625 nm)	NA	NA	NA	NA	± 0.05 dB (0-20 dB attenuation) ± 0.10 dB (20-30 dB attenuation)
Maximum optical input power	200 mW	200 mW	200 mW	200 mW	1000 mW
Recalibration period (recommended)	2 years				
Polarization dependent loss <sup>4,5</sup>	0.03 dB typical, 0.08 dB maximum				
Beam block attenuation	> 90 dB				
Input voltage	90-240 V AC, 50-60 Hz				
Power consumption	80 VA maximum				
Dimensions W x H x D	21.2 x 8.9 x 35.5 cm 19 inch (48.26 cm) rack mounting 2U high				
Weight	4 kg				
Operating temperature	0 to 40 °C				
Storage temperature	- 40 to 60 °C				
Humidity	maximum 90 % up to 40 °C				

1. The attenuation range is a continuous function of wavelength.
2. At constant temperature, wavelength, and polarization state after half hour warm-up.
3. With optimization of the calibration wavelength or user slope. If optimization is not performed, accuracy is the greater of ± 0.1 dB or ± 0.004 dB/dB from 1260-1360 nm and from 1450-1570 nm. At other wavelengths, the accuracy is the greater of ± 0.1 dB or ± 0.015 dB/dB if optimization is not performed.
4. Measured at 23 °C with a laser source.
5. Not including connectors, switch, or coupler (if installed).
6. Over 850-1600 nm. Insertion loss is typically highest at wavelength extremes.
7. Total of discrete reflections. Does not include distributed reflection in fiber.
8. From 1375-1670 nm.
9. Relative to reference 0 dB setting.

## Ordering Information

### Sample Order: HA097+28KFA1

HA    +2

code	model
01	HA1 (high resolution, 1270-1700 nm)
02	HA2 (high power, wavelength flat)
09	HA9 (1200-1700 nm)
9P	HA9P (Flexcor 1060, 980-1100 nm)
9W	HA9W (750-1700 nm)

code	fiber type (μm)
1	50/125 (HA9 and HA9W only)
2	62.5/125 (HA9 and HA9W only)
7	9/125
8	Flexcor 1060 (HA9P only)

code	built-in options
0	None
1	50/50 coupler (HA1 and HA9 only)
4	2/98 coupler (HA1 and HA9 only)
5	30/70 coupler (HA1 and HA9 only)
8	1:2 switch (HA1 and HA9 only)
9	10/90 coupler (HA1 and HA9 only)

code	port type
1	Bulkheads on front
2	Bulkheads on back
3	Pigtails on front
4	Pigtails on back
7	UCA Bulkheads on front

code	connector type (all ports)
NC	No connector
FP	FC/HPC
FA	FC/APC
SC	SC/HPC
SU	SC/APC
SP	ST/HPC

code	return loss
K	Low 45 dB (HA9 and HA9W only)
A	Analog

Flexcor is a registered trademark of Corning Incorporated.

UL is a registered trademark of Underwriters Laboratories Inc.

ST is a registered trademark of Lucent Technologies.

All statements, technical information and recommendations related to the products herein are based upon information believed to be reliable or accurate. However, the accuracy or completeness thereof is not guaranteed, and no responsibility is assumed for any inaccuracies. The user assumes all risks and liability whatsoever in connection with the use of a product or its application. JDS Uniphase reserves the right to change at any time without notice the design, specifications, function, fit or form of its products described herein, including withdrawal at any time of a product offered for sale herein. JDS Uniphase makes no representations that the products herein are free from any intellectual property claims of others. Please contact JDS Uniphase for more information. JDS Uniphase, the JDS Uniphase logo and the JDS Uniphase Instrumentation logo are trademarks of JDS Uniphase Corporation. Other trademarks are the property of their respective holders. 2002 © JDS Uniphase Corporation. All rights reserved. Printed in Canada. 10109631 Rev. 000 03/02 Preliminary

Indicate your requirements by selecting one option from each configuration table. Print the corresponding codes in the available boxes to form your part number.

#### CORPORATE HEAD OFFICES

8:00 am - 5:00 pm ET  
3000 Merivale Rd  
Ottawa, Ontario  
Canada K2G 6N7

TEL: (613) 727.1304  
FAX: (613) 727.8284

#### GLOBAL SALES AND CUSTOMER SERVICE

##### North America:

8:00 am - 8:00 pm ET  
TEL: 800-871-8537 (Toll Free in North America)

##### Outside North America:

8:00 am - 8:00 pm ET  
TEL: 800-8735-5378 (Toll Free International)  
FAX: 800-7777-5378

#### INSTRUMENTATION GROUP

E-MAIL: instruments@jdsu.com  
WEB: www.jdsu.com/instruments  
CORPORATE WEB: www.jdsu.com